

# INDUSTRIAL PC MYGICA APC395X3

## **GENERAL DESCRIPTION**

Is a powerful multimedia Android playback box and an entry level ARM.

# Android PC with below new features:

- (I) Quad-core ARM Cortex-A55 CPU, Android 9.0 OS
- (II) Support 2GB DDR3, 8GB eMMc flash, external expansion storage Micro SD card (Max 128G)
- (III) One USB3.0 Type-A and one USB2.0 Type A, Micro SD Card slot
- (IV) Built-in Wi-Fi (Support 2.4G and 5.8G)/BT4.2, 10M/100M/1000M LAN interface
- (V) One HDMI-out, Up to 3840 \* 2160 60hz (VI) Support RS-232/Audio Out (Pins shared)
- (VI) Applicable to commercial display player



### **FEATURES**

FEATORES					
CHIPSET		Amlogic S905X3			
MARKET AREA		Global			
Processor		os		Android 9.0	
		CPU		Quad-core ARM Cortex-A55	
		GPU		ARM Mali-G31 MP2 850MHz	
		DDR3		2GB(1G optioal)	
		EMMC FLASH		8GB(16G Optional)	
NETWORK	Ethernet	RJ45, 10/100/1000M			
	WiFi	WIFI/802.11.AC			
	Bluetooth	BT4.2			
Interface		HDMI Out	*1	*1	
		USB 3.0	*1		
		USB 2.0	*1		
		SD	*1		
		RS-232/Audio Out	*1 (shared in one slot)		
		DC IN	*1	*1	
Adapter		DC5V / 2A			
Dimensions		105x100x27mm			
Accessory		Adapter*1			











No.	Name	Description
1	Power Key	*1
2	IR	*1
3	Net LED	*1
4	SD Card Slot	*1
5	Power LED	*1(Blue/Green)
6	USB2.0	*1
7	USB3.0	*1
8	DC IN	*1(5V/2A)
9	AV OUT/RS-232	Shared in one Slot
10	HDMI Out	*1
11	RJ45	*1
12	Antenna	WIFI Antenna

#### SUPPORT FORMATS

#### **Audio Decoder**

Supports MP3,AAC,WMA,RM,FLAC,Ogg and programmable with 7.1/5.1 down-mixing

#### Video Decoder

VP9 Profile-2 up to 4Kx2K@60fps

H.265 HEVC MP-10@L5.1 up to 4kx2k@60fps

H.264 AVC HP @L5.1 up to 4kx2k@30fps

H.264 MVC up to 1080P@60fps

MPEG-1 MP/HL up to 1080P@60fps

MPEG-2 MP/HL up to 1080P@60fps

MPEG-4 ASP@L5 up

WMV/VC-1 SP/MP/AP up to 1080P@60fps

RealVideo 8/9/10 up to 1080P@60fps

Support .mkv/.wmv/.mpg/.mpeg/.dat/.avi/.mov/.iso/.mp4/.rm/.jpg file formats

#### Precautions for use

- 1.Relative humidity: ≤80%.
- Operation temperature: 0~ 50℃
- 3.Do not squeeze, distort or disassemble the PC.
- 4. Keep the Board away from static electricity .
- 5.Keep the Board away from water and other liquid.
- 6.Don't use long connect wires which may affect performance and image quality.